



VPO
Visual Persistence Oscilloscope

GDS-3000 Series

FEATURES

- 350/250/150MHz Bandwidth,
- Dual Sampling Modes: 5GSa/s Real-Time Sampling Rate and 100GSa/s Equivalent Time Sampling Rate
- 25k points Memory for each input channel
- VPO (Visual Persistence Oscilloscope) Technology to Display Less-Frequently-Appeared Signals
- 8" 800 x 600 High Resolution TFT LCD Display
- Unique Split Screen System with Independent Setting for Each Signal Channel
- Three Input Impedance Selection: 50Ω /75Ω /1MΩ
- Optional Power Measurement Software for Power Supply Measurement and Analysis
- Optional Serial BUS Triggering, Decoding Software Supporting I²C, SPI and UART



Front



Rear Panel

The GDS-3000 Series digital storage oscilloscope is a full-featured and powerful tool that allows you to tackle complex measurement issues with ease.

The GDS-3000 Series, carrying a maximum bandwidth of 350MHz, is equipped with a real-time sampling rate up to 5GSa/s and an equivalent-time sampling rate of 100GSa/s. The large 8-inch SVGA TFT LCD screen, combined with the advanced digital signal processing technology – VPO, provides meticulous detail and clarity for the displayed waveforms. The GDS-3000 Series gives you confidence not to miss any part of the test signal in the product verification and debugging stages and allows you to speed up your task without hesitation.

Rich Features

With widespread applications of embedded system using serial bus communications, resolving unexpected issues, such as propagation delay and bus contention, is often a challenge to design and testing engineers. The GDS-3000 Series provides (optional) design and testing engineers with powerful tools for the communication analysis and debugging of the most popular serial interface projects including I²C, SPI and UART.

To fulfill the increasing power measurement demands, as a green energy trend, GDS-3000 provides an embedded power-measurement software (optional), which includes measurements of Power Quality, Harmonics, Ripple and Inrush Current, meeting requirements of most power measurement standards.

Convenient platform

With 5GSa/s sampling and Visual Persistence Oscilloscope (VPO) technology, GDS-3000 displays waveforms truthfully and captures less-frequently-appeared signals, like glitches or runts, simultaneously without missing any spot of waveform information. A unique Split-screen feature allows each input channel to be operated independently with respective setting and waveform display. This gives users flexibility to use GDS-3000 Series as a multi-scope-in-one DSO.

To alleviate the burden of manual operation and to reduce human error, additional features such as auto range are used to automatically adjust the horizontal and vertical scale of a displayed signal so that waveforms are displayed with the best possible viewing ratio.

The I/O Interfaces give you a good range of choices and convenience. In the front panel, a USB host port is used for easy data access. And in the rear panel, another USB port can be used for remote control or for screen printout directly from PictBridge compatible printers. In addition, RS-232 and LAN interfaces provide the flexibility supporting broad range of applications. The SVGA video output port allows you to display the screen on an external projector or monitor for information sharing and discussion.

Unique Signal Processing -VPO

The GDS-3000 VPO (Visual Persistence Oscilloscope) technology adopts a very unique signal-processing design. To significantly increase the data processing speed and the waveform capture rate, GDS-3000 uses FPGA platform to replace conventional serial microprocessor architecture. This unique technology allows the GDS-3000 Series to show waveforms in a fashion like that of an analog oscilloscope. The VPO three dimension waveform display, containing the information of amplitude, time and intensity, provides more useful signal contents for the analysis of rapid-changed events, such as video, jitter and infrequent signals.

APPLICATIONS

- Industrial and Educational R&D Labs
- Product Testing and Quality Assurance
- Power Supply and Serial BUS Design
- System Integration & Debugging
- Maintenance & Repair Service

SPECIFICATIONS

		GDS-3152	GDS-3154	GDS-3252	GDS-3254	GDS-3352	GDS-3354	
VERTICAL	Channels	2Ch+EXT	4Ch+EXT	2Ch+EXT	4Ch+EXT	2Ch+EXT	4Ch+EXT	
	Bandwidth	DC~150MHz(-3dB)	DC~150MHz(-3dB)	DC~250MHz(-3dB)	DC~250MHz(-3dB)	DC~350MHz(-3dB)	DC~350MHz(-3dB)	
VERTICAL	Rise Time	2.3ns	2.3ns	1.4ns	1.4ns	1ns	1ns	
	Vertical Resolution	8 bits						
	Vertical Resolution(1MΩ)	2mV~5V/div						
	Vertical Resolution(50/75Ω)	2mV~1V/div						
	Input Coupling	AC, DC, GND						
	Input Impedance	1M Ω // 16pF						
	DC Gain Accuracy	$\pm(3\% \times \text{Readout} + 0.1\text{div} + 1\text{mV})$						
	Polarity	Normal, Invert						
	Maximum Input Voltage(1MΩ)	300V (DC+AC Peak), CAT I						
	Maximum Input Voltage(50/75Ω)	5 Vrms max, CAT I						
	Offset Position Range	2mV/div ~ 100mV/div : $\pm 0.5\text{V}$; 200mV/div ~ 5V/div : $\pm 25\text{V}$						
	Bandwidth Limit	20MHz/100MHz/200MHz (-3dB)						
	Waveform Signal Process	Add, subtract, multiply, and divide waveforms, FFT, FFTrms; FFT : Spectral magnitude. Set FFT Vertical Scale to Linear RMS or dBV RMS, and FFT Window to Rectangular, Hamming, Hanning, or Blackman-Harris.						
	TRIGGER	Source	CH1, CH2, Line, EXT					
		Trigger Mode	Auto (supports Roll Mode for 100 ms/div and slower), Normal, Single Edge, Pulse Width, Video, Runt, Rise & Fall, Alternate,					
Trigger Type		Event-Delay(1~65,535 events), Time-Delay(10ns~10s) (for 4-channel models only), I ² C, SPI, UART(optional)						
Trigger Holdoff Range		10ns ~ 10s						
Coupling Sensitivity		AC, DC, LF rej., Hf rej., Noise rej. DC~30MHz Approx. 0.5div or 5mV; 30MHz~150MHz Approx. 1.5div or 15mV; 150MHz~350MHz Approx. 2div or 20mV						
EXT TRIGGER	Range	$\pm 15\text{V}$						
	Sensitivity	DC ~ 30MHz Approx. 50mV; 30MHz ~ 150MHz Approx. 100mV 150MHz ~ 250MHz Approx. 150mV; 250MHz ~ 350MHz Approx. 150mV						
HORIZONTAL	Input Impedance	1M Ω $\pm 3\%$, ~16pF						
	Range	1ns/div ~ 50s/div (1-2-5 increments); ROLL : 100ms/div ~ 100s/div						
	Pre-trigger Accuracy	10 div maximum 1,000 div ± 20 ppm over any ≥ 1 ms time interval						
X-Y MODE	X-Axis Input/Y-Axis Input Phase Shift	Channel 1; Channel 3/Channel 2; Channel 4 $\pm 3^\circ$ at 100kHz						
SIGNAL ACQUISITION	Real Time Sample Rate	2.5GSa/s	5GSa/s	2.5GSa/s	5GSa/s	5GSa/s	5GSa/s	
	ET Sample Rate	100GSa/s maximum for all models						
	Record Length	25k points						
	Acquisition Mode	Normal, Average, Peak Detect, High Resolution, Single						
Cursors AND MEASUREMENT	Peak Detection	2ns (Max.) Normal: Acquire sampled values; Average: From 2 ~ 256 waveforms included in average; Peak Detect: Captures glitches as narrow as 2 ns at all sweep speeds; Hi Res: Real-time boxcar averaging reduces random noise and increases vertical resolution.						
	Cursors	Amplitude, Time, Gating available 28 sets: Vpp, Vamp, Vavg, Vrms, Vhi, Vlo, Vmax, Vmin, Rise Preshoot/ Overshoot, Fall Preshoot/Overshoot, Freq, Period, Rise Time, Fall Time, Positive Width, Negative Width, Duty Cycle, Phase, and eight different delay measurements (FRR, FRF, FFR, FFF, LRR, LRF, LFR, LFF)						
POWER MEASUREMENTS (OPTION)	Automatic Measurement	Voltage difference between cursors (ΔV) Time difference between cursors (ΔT) 6 digits, range from 2Hz minimum to the rated bandwidth						
	Cursors measurement Auto counter	VRMS, VCrest Factor, Frequency, IRMS, ICrest Factor, TruePower, Apparent Power, Reactive Power, Power Factor, Phase Angle. Freq, Mag, Mag rms, Phase, THD-F, THD-R, RMS V ripple, I ripple First peak, second peak						
CONTROL PANEL FUNCTION	Power Quality Measurements	Single-button, automatic setup of all channels for vertical, horizontal and trigger systems, with undo autoset						
	Harmonics	Allow users to quickly move from test point to test point without having to reset the oscilloscope for each test point						
DISPLAY SYSTEM	Ripple Measurements	20set						
	In-rush current	24set						
INTERFACE	Autoset	8" TFT LCD SVGA color display(LED Back-light)						
	Auto-Range	800 horizontal x 600 vertical pixels (SVGA)						
	Save Setup	Sin(x)/x & Equivalent Time Sampling						
	Save Waveform	Dots, vectors, variable persistence, infinite persistence						
	Display Graticul	8 x 10 divisions						
POWER SOURCE MISCELLANEOUS	Display Brightness	Adjustable						
	RS-232C	DB-9 male connector						
	USB Port	2 sets USB 2.0 High-speed host port; 1 set USB High-speed 2.0 device port						
	Ethernet Port	RJ-45 connector, 10/100Mbps						
	SVGA Video Port	DB-15 female connector, monitor output for display on SVGA monitors						
	GPIO	USB-to-GPIO converter (Option)						
	Go/NoGo BNC	5V Max/10mA TTL Open collector output						
POWER SOURCE MISCELLANEOUS	Internal Flash Disk	64MB						
	Kensington Style Lock	Rear-panel security slot connects to standard Kensington-style lock						
POWER SOURCE MISCELLANEOUS	Line Voltage Range	3.5mm stereo jack for Go/NoGo audio alarm						
	Multi-Language Menu	AC 100V ~ 240V, 48Hz ~ 63Hz, Auto selection						
POWER SOURCE MISCELLANEOUS	On-Line Help	Available						
	Time clock	Available						
DIMENSIONS & WEIGHT		Time and Data, Provide the Data/Time for saved data						
		400(W) X 200(H) X 130(D)mm, Approx. 4 kg						

Specifications subject to change without notice. DS-3000GD1DH

ORDERING INFORMATION

GDS-3352	350MHz, 2-Channel, Visual Persistence DSO
GDS-3354	350MHz, 4-Channel, Visual Persistence DSO
GDS-3252	250MHz, 2-Channel, Visual Persistence DSO
GDS-3254	250MHz, 4-Channel, Visual Persistence DSO
GDS-3152	150MHz, 2-Channel, Visual Persistence DSO
GDS-3154	150MHz, 4-Channel, Visual Persistence DSO

ACCESSORIES

User manual x 1, Power cord x 1
 GTP-151R:150MHz(10:1/1:1) Switchable Passive Probe for GDS-3152/3154(one per channel)
 GTP-251R:250MHz(10:1/1:1) Switchable Passive Probe for GDS-3252/3254(one per channel)
 GTP-351R:350MHz(10:1/1:1) Switchable Passive Probe for GDS-3252/3254(one per channel)

Global Headquarters

U.S.A. Subsidiary

OPTION

DS3-PWR Power analysis software: Power quality/Harmonic/Ripple/In-rush current measurements
DS3-SBD Series Bus analysis software: I²C/SPI/UART/RS-232/422/485(for 4-channel models only)
Opt.01 GPIO to USB Converter

OPTIONAL ACCESSORIES

GDP-025	25MHz high voltage differential probe
GDP-050	50MHz high voltage differential probe
GDP-100	100MHz high voltage differential probe
GCP-530	50MHz/30A Current probe
GCP-1030	100MHz/30A Current probe
GCP-206P	Power supply for current probe (2 input channel)
GCP-425P	Power supply for current probe (4 input channel)

FREE DOWNLOAD

PC Software FreeWave software **Driver** USB driver; LabView Driver

GW INSTEK

Made to Measure Since 1975

www.gwinstek.com

Distributed by:
www.SignalTestInc.com <<http://www.SignalTestInc.com>>
 1529 Santiago Ridge Way
 San Diego, CA 92154 USA.
 Sales@SignalTestInc.com

SIGNAL TEST
 New & Used Test Equipment

Simply Reliable
 Our lowest TCO helps you control costs with reliable products and services.