

Active Probe for SMDs

P6245 • P6243 Data Sheet



P6243

Features & Benefits

P6245

- ≥ 1.5 GHz Bandwidth (Typical, Probe Only)
- ≤ 1 pF Input Capacitance
- 1 M Ω Input Resistance
- Direct Access to SMDs as Small as 0.5 mm Pitch
- Measures CMOS, BiCMOS, ECL, GaAs, and TTL Logic

P6243

- 1 GHz Bandwidth (probe only)
- ≤ 1 pF Input Capacitance
- 1 M Ω Input Resistance
- Direct Access to SMDs as Small as 0.5 mm Pitch
- Measures CMOS, BiCMOS, ECL, GaAs, and TTL Logic
- Low-mass Probe Head/Cable
- No Additional Power Supplies or Cables Are Required with TEKPROBE™ BNC Interface

Applications

- High-speed Digital Systems Design
- Component Design/Characterization
- Manufacturing Engineering and Test
- Educational Research

P6245 and P6243 Active Probes for TEKPROBE BNC Interfaces

P6245

The P6245 Active FET probe achieves high-speed signal acquisition by solving three traditional problems:

- Lower DUT loading (≤ 1 pF/1 M Ω probe loading)
- Direct and easy access to SMDs
- Access DUT signals and scope bandwidth for TDS600/700/3000/5000/6000/7000*¹ and CSA7000 scopes up to 1 GHz bandwidths

The P6245 and P6243 Active probes provide the electrical and mechanical performance required for today's digital systems designs. No additional power supplies or cables are required when used with TEKPROBE BNC oscilloscopes. Both the P6245 and P6243 achieve high-speed signal acquisition and low circuit loading, required for solving today's problems faced by designers.

The small compact probe head and versatile attachment accessories allow direct connection to the device under test.

The P6245 and P6243 Active Probes provide scope bandwidth at the probe tip for the TDS500/600/700; the P6243 provides scope bandwidth at the probe tip for the TDS3000 Series scope up to 1 GHz bandwidth.

*¹ Some TDS6000 or TDS7000 oscilloscopes require a TCA-BNC adapter.

P6243

The P6243 Active FET probe is the high-performance probing solution for 500 MHz oscilloscopes. The P6243 has a probe only bandwidth of 1 GHz and will provide a 500 MHz system bandwidth when used with Tektronix' full line of 500 MHz oscilloscopes. In addition, the P6243 is powered by the TEKPROBE BNC interface, eliminating the need for additional power supplies and cables when used with TEKPROBE BNC oscilloscopes.

The P6243 offers superior signal acquisition on surface mount devices compared to the much higher capacitive loading of passive probes. The P6243 has ≤ 1 pF capacitive loading which allows it to measure high-speed signals without affecting the signal or device under test. Furthermore, the included accessories and adapters allow for easy attachment to SMDs.

Characteristics

Probe Type	P6243	P6245
Cable Length	1.3 m	1.3 m
Attenuation	10X	10X
Bandwidth in GHz (Probe Only)	1 GHz	1.5 GHz
Rise Time	<350 ps	<250 ps
Input C in pF	≤ 1 pF	≤ 1 pF
Input R in Ω	1 M Ω	1 M Ω
Linear Dynamic Range	± 8 V	± 8 V
DC Offset Range	N/A	10 V
Max Voltage (Nondestruct) (DC+PkAC)	± 15 V	± 15 V
Propagation Delay	5.3 ns ± 200 ps	5.3 ns ± 200 ps

Ordering Information

P6245

Active Probe.

P6243

Active Probe.

Included Accessories

Description	Quantity P6245	Quantity P6243	Reorder Part Number
Solderable Probe Tips	10 each	10 each	131-5638-xx (Pkg. of 10)
1 in. Ground Lead	2 each	2 each	196-3439-xx (Pkg. of 10)
6 in. Ground Lead	2 each	1 each	196-3436-xx
3 in. Ground Lead	2 each	1 each	196-3437-xx
Y Lead Adapters	2 each	1 each	196-3463-xx
SMT KlipChip™ Adapter	4 each	2 each	206-0364-xx
Color Coding Clips, 2 each 5 colors	1 each	1 each	016-1315-xx
Right Angle Square Pin Adapter	2 each	1 each	214-4227-xx
100 Mil Square Pin Adapter	2 each	1 each	131-5777-xx

Service

Opt. C3 – Calibration Service 3 Years

Opt. C5 – Calibration Service 5 Years

Opt. D1 – Calibration Data Report

Opt. D3 – Calibration Data Report 3 Years (with Opt. C3)

Opt. D5 – Calibration Data Report 5 Years (with Opt. C5)

Opt. R3 – Repair Service 3 Years

Opt. R5 – Repair Service 5 Years

Recommended Accessories

SMD Probing Adapters*¹

SureFoot® Adapters –

50 mil pitch. Order SF501.

25 mil and 0.65 mm pitch. Order SF502.

0.5 mm pitch. Order SF503.










IC Grabber – 0.5 mm pitch. Order 013-0309-00 (See SureFoot Adapters).

*¹ See SureFoot for complete SMD Adapters information.

Please see the General Customer Information pages for additional information.




P6245 / P6243
Part Reorder 1-800-833-9200

 <p>131-5777-xx 100 mil Square Pin Ground Adapter</p>	 <p>214-4227-xx Right Angle Square Pin Adapter</p>	 <p>Tektronix SF503 Solderless 0.5 mm SET OF 12 PAT. 5,387,872</p>	 <p>Tektronix SF502 Solderless 25mil SET OF 12 PAT. 5,387,872</p>	 <p>Tektronix SF501 Solderless-ORANGE 50mil SET OF 12 PAT. 5,387,872</p>
 <p>131-5638-xx Solderable Probe Tips</p>		 <p>016-1315-xx Color Coding Clips</p>		
 <p>206-0364-xx (1 each) SMT KlipChip</p>				
 <p>196-3410-xx Ground Lead set</p> <p>6" Ground Leads 196-3436-xx</p> <p>1" Z Ground Leads 196-3439-xx</p> <p>3" Ground Leads 196-3437-xx</p> <p>Y-Leads 196-3463-xx</p>				



SF500 Series (Surefoot)



IC Grabber 013-0309-00



Product(s) are manufactured in ISO registered facilities.

Contact Tektronix:

ASEAN / Australasia (65) 6356 3900
Austria +41 52 675 3777
Balkans, Israel, South Africa and other ISE Countries +41 52 675 3777
Belgium 07 81 60166
Brazil +55 (11) 40669400
Canada 1 (800) 661-5625
Central East Europe, Ukraine, and the Baltics +41 52 675 3777
Central Europe & Greece +41 52 675 3777
Denmark +45 80 88 1401
Finland +41 52 675 3777
France +33 (0) 1 69 86 81 81
Germany +49 (221) 94 77 400
Hong Kong (852) 2585-6688
India (91) 80-42922600
Italy +39 (02) 25086 1
Japan 81 (3) 6714-3010
Luxembourg +44 (0) 1344 392400
Mexico, Central/South America & Caribbean 52 (55) 54247900
Middle East, Asia, and North Africa +41 52 675 3777
The Netherlands 090 02 021797
Norway 800 16098
People's Republic of China 86 (10) 6235 1230
Poland +41 52 675 3777
Portugal 80 08 12370
Republic of Korea 82 (2) 6917-5000
Russia & CIS +7 (495) 7484900
South Africa +27 11 206 8360
Spain (+34) 901 988 054
Sweden 020 08 80371
Switzerland +41 52 675 3777
Taiwan 886 (2) 2722-9622
United Kingdom & Ireland +44 (0) 1344 392400
USA 1 (800) 426-2200

For other areas contact Tektronix, Inc at: 1 (503) 627-7111

Updated 30 October 2008

For Further Information. Tektronix maintains a comprehensive, constantly expanding collection of application notes, technical briefs and other resources to help engineers working on the cutting edge of technology. Please visit www.tektronix.com



Copyright © Tektronix, Inc. All rights reserved. Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supersedes that in all previously published material. Specification and price change privileges reserved. TEKTRONIX and TEK are registered trademarks of Tektronix, Inc. All other trade names referenced are the service marks, trademarks, or registered trademarks of their respective companies.

29 May 2009

60W-13989-4

www.tektronix.com



Distributed by:
www.SignalTestInc.com
1529 Santiago Ridge Way
San Diego, CA 92154 USA.
Sales@SignalTestInc.com

